

Package ‘CNORode’

October 8, 2015

Type Package

Title ODE add-on to CellNOptR

Version 1.10.0

Date 2014-01-10

Author David Henriques, Thomas Cokelaer

Maintainer David Henriques <davidpcnet@hotmail.com>

biocViews CellBasedAssays, CellBiology, Proteomics, Bioinformatics,
TimeCourse

Description ODE add-on to CellNOptR

License GPL-2

LazyLoad yes

Depends CellNOptR (>= 1.5.14), genalg

Enhances MEIGOR

NeedsCompilation yes

R topics documented:

cnolistCNORodeExample	2
CNORode	2
createLBodeContPars	3
defaultParametersGA	5
defaultParametersSSm	6
getLBodeContObjFunction	7
getLBodeDataSim	8
getLBodeMINLPObjFunction	10
getLBodeModelSim	11
getLBodeSimFunction	13
getStates	14
incidence2Adjacency	15
indices	15
minlpLBodeSSm	16
model	18

parEstimationLBode	18
parEstimationLBodeGA	20
parEstimationLBodeSSm	22
plotLBodeFitness	24
plotLBodeModelSim	26
simdata2cnolist	27
simulate	28

Index	30
--------------	-----------

cnolistCNORodeExample *A cnolist from CellNOptR*

Description

A cnolist from CellNOptR to use with provided CNORode examples.

CNORode *Logic based ODE extension for CellNOptR*

Description

This package is used for the simulation and fitting of logic based ODE models based on the Odefy approach.

Details

Package:	CNORode
Type:	Package
Version:	1.2.0
Date:	2012-03-14
License:	GPL-3
LazyLoad:	yes

Author(s)

David Henriques, Thomas Cokelaer Maintainer: David Henriques <dhenriques@ebi.ac.uk>

References

Dominik Wittmann, Jan Krumsiek, Julio S. Rodriguez, Douglas Lauffenburger, Steffen Klamt, and Fabian Theis. Transforming boolean models to continuous models: methodology and application to t-cell receptor signaling. *BMC Systems Biology*, 3(1):98+, September 2009.

Egea, J.A., Maria, R., Banga, J.R. (2010) An evolutionary method for complex-process optimization. *Computers & Operations Research* 37(2): 315-324.

Egea, J.A., Balsa-Canto, E., Garcia, M.S.G., Banga, J.R. (2009) Dynamic optimization of nonlinear processes with an enhanced scatter search method. *Industrial & Engineering Chemistry Research* 49(9): 4388-4401.

Jan Krumsiek, Sebastian Polsterl, Dominik Wittmann, and Fabian Theis. Odefy - from discrete to continuous models. *BMC Bioinformatics*, 11(1):233+, 2010.

R. Serban and A. C. Hindmarsh, "CVODES: the Sensitivity-Enabled ODE Solver in SUNDIALS," Proceedings of IDETC/CIE 2005, Sept. 2005, Long Beach, CA. Also available as LLNL technical report UCRL-JP-200039.

C. Terfve, T. Cokelaer, A. MacNamara, D. Henriques, E. Goncalves, MK. Morris, M. van Iersel, DA Lauffenburger, J. Saez-Rodriguez. CellNOptR: a flexible toolkit to train protein signaling networks to data using multiple logic formalisms. *BMC Systems Biology*, 2012, 6:133:

See Also

[CellNOptR](#), [parEstimationLBode](#), [getLBodeModelSim](#), [parEstimationLBode](#) [plotLBodeFitness](#).

createLBodeContPars *Create a list with ODE parameter information needed to perform parameter estimation*

Description

Creates a list with the continuous parameters to simulate the model, upper and lower bounds for the parameter estimation, parameters names, indices of the parameters and other information.

Usage

```
createLBodeContPars(model, LB_n = 1, LB_k = 0.1, LB_tau = 0.01,
  UB_n = 5, UB_k = 0.9, UB_tau = 10, default_n = 3, default_k = 0.5,
  default_tau = 1, LB_in = c(), UB_in = c(), opt_n = TRUE, opt_k = TRUE,
  opt_tau = TRUE, random = FALSE)
```

Arguments

model	The logic model to be simulated.
LB_n	A numeric value to be used as lower bound for all parameters of type n.
LB_k	A numeric value to be used as lower bound for all parameters of type k.
LB_tau	A numeric value to be used as lower bound for all parameters of type tau.
UB_n	A numeric value to be used as upper bound for all parameters of type n.
UB_k	A numeric value to be used as upper bound for all parameters of type k.
UB_tau	A numeric value to be used as upper bound for all parameters of type tau.
default_n	The default parameter to be used for every parameter of type n.

default_k	The default parameter to be used for every parameter of type k.
default_tau	The default parameter to be used for every parameter of type tau.
LB_in	An array with the the same length as ode_parameters\$parValues with lower bounds for each specific parameter.
UB_in	An array with the the same length as ode_parameters\$parValues with upper bounds for each specific parameter.
opt_n	Add all parameter n to the index of parameters to be fitted.
opt_k	Add all parameter k to the index of parameters to be fitted.
opt_tau	Add all parameter tau to the index of parameters to be fitted.
random	logical value that determines that a random solution is for the parameters to be optimized.

Value

parNames	An array containing the names of the parameters.
parValues	An array containing the values of the parameters, in the same order as the names.
index_opt_pars	An array containing the indexes for the parameters to be fitted.
index_n	An array containing the indexes of the parameters of type n.
index_k	An array containing the indexes of the parameters of type k.
index_tau	An array containing the indexes of the parameters of type tau.
LB	An array containing the lower bound for each parameter.
UB	An array containing the upper bound for each parameter.

Author(s)

David Henriques, Thomas Cokelaer

Examples

```
library(CNORode)
data("ToyCN0list", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");
ode_parameters=createLBodeContPars(model, opt_n=FALSE, default_n=2,
random=TRUE, LB_k=0.25, UB_k=0.8, LB_tau=0.01, UB_tau=10);
```

defaultParametersGA *Create default options to perform parameter estimation with a genetic algorithm.*

Description

This function returns a list with several arguments for performing parameter estimation with the genetic algorithm from the package `genalg`.

Usage

```
defaultParametersGA()
```

Value

```
mutationChance NA
popSize        200
iters          100
elitism        NA
time           1
monitor        TRUE
verbose        0
transfer_function
               3
reltol         1e-04
atol           0.001
maxStepSize    Inf
maxNumSteps    1e+05
maxErrTestsFails
               50
nan_fac = 1    0
```

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [parEstimationLBode](#) [parEstimationLBodeGA](#)

defaultParametersSSm *Create default options to perform parameter estimation with scatter search meta-heuristic.*

Description

This function returns a list with several arguments for performing parameter estimation with scatter search meta-heuristic algorithm from the package `essR`.

Usage

```
defaultParametersSSm()
```

Value

maxeval	Inf
maxtime	100
ndiverse	NULL
dim_refset	NULL
local_solver	NULL
verbose	0
transfer_function	3
reltol	1e-04
atol	0.001
maxStepSize	Inf
maxNumSteps	1e+05
maxErrTestsFails	50
nan_fac	1

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [parEstimationLBode](#) [parEstimationLBodeSSm](#)

 getLBodeContObjFunction

Returns the objective function to perform parameter estimation.

Description

This function configures returns the objective function that can be used to evaluate the fitness of a logic based ODE model using a particular set of parameters. This function can be particularly useful if you are planning to couple a nonlinear optimization solver. The returned value of the objective function corresponds to the mean squared value normalized by the number of data points.

Usage

```
getLBodeContObjFunction(cnolist, model, ode_parameters, indices=NULL, time = 1,
  verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001, maxStepSize = Inf,
  maxNumSteps = 1e+05, maxErrTestsFails = 50, nan_fac = 1, useVariances = F, initial_state=0.1)
```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
time	An integer with the index of the time point to start the simulation. Default is 1.
verbose	A logical value that triggers a set of comments.
transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.
maxStepSize	The maximum step size allowed to ODE solver.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.
maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.
nan_fac	A penalty for each data point the model is not able to simulate. We recommend higher than 0 and smaller than 1.
useVariances	if True, use the variance in the fitness
initial_state	initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Details

Check [CellNOptR](#) for details about the cnoList and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a function to evaluate the model fitness. This function receives a vector containing both continuous parameters and integer values representing which reactions should be kept in the model.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [createLBodeContPars](#)

Examples

```
library(CNORode)
data("ToyCNOlist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");

ode_parameters=createLBodeContPars(model, random=TRUE);
minlp_obj_function=getLBodeContObjFunction(cnoListCNORodeExample, model,ode_parameters,indices);

x=ode_parameters$parValues;

f=minlp_obj_function(x);
```

getLBodeDataSim

Simulate value signals a CNO list With Logic-Based ODEs.

Description

This function receives a set of inputs, namely the cnoList and the model and returns a list with the same size of the cnoList\$valueSignals.

Usage

```
getLBodeDataSim(cnoList, model, ode_parameters = NULL, indices = NULL,
timeSignals=NULL, time = 1, verbose = 0, transfer_function = 3,
reltol = 1e-04, atol = 0.001, maxStepSize = Inf, maxNumSteps = 1e+05,
maxErrTestsFails = 50, initial_state=0.1)
```


Arguments

<code>cnolist</code>	A list containing the experimental design and data.
<code>model</code>	A list with the ODEs parameter information. Obtained with createLBodeContPars .
<code>ode_parameters</code>	A list with the ODEs parameter information. Obtained with <code>makeParameterList</code> function.
<code>indices</code>	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
<code>timeSignals</code>	An array containing a different timeSignals. If you use this argument, it will also modify the dimensions from <code>valueSignals</code> .
<code>time</code>	An integer with the index of the time point to start the simulation. Default is 1.
<code>verbose</code>	A logical value that triggers a set of comments.
<code>transfer_function</code>	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
<code>reltol</code>	Relative Tolerance for numerical integration.
<code>atol</code>	Absolute tolerance for numerical integration.
<code>maxStepSize</code>	The maximum step size allowed to ODE solver.
<code>maxNumSteps</code>	The maximum number of internal steps between two points being sampled before the solver fails.
<code>maxErrTestsFails</code>	Specifies the maximum number of error test failures permitted in attempting one step.
<code>initial_state</code>	initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Details

Check [CellNOptR](#) for details about the `cnolist` and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a list with simulated data that has the same structure as the `cnolist$valueSignals`. One matrix for each time-point.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [parEstimationLBode](#) [parEstimationLBodeSSm](#)

Examples

```
library(CNORode)
data("ToyCNolist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");
dataSimulation=getLBodeDataSim(cnolistCNORodeExample, model, indices=indices);
```

```
getLBodeMINLPObjFunction
```

Get the objective function to evaluate the fitness of a given model structure and set of parameters.

Description

This function configures returns the objective function that can be used to evaluate the fitness of a logic based ODE model using a particular set of parameters and model structure. This function can be particular useful if you are planing to couple a mixed integer nonlinear programming optimization solver. The returned value of the objective function corresponds to the mean squared value.

Usage

```
getLBodeMINLPObjFunction(cnolist, model, ode_parameters, indices=NULL, time = 1,
  verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001, maxStepSize = Inf,
  maxNumSteps = 1e+05, maxErrTestsFails = 50, nan_fac = 1)
```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with indexFinder function from CellNOptR .
time	An integer with the index of the time point to start the simulation. Default is 1.
verbose	A logical value that triggers a set of comments.
transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.
maxStepSize	The maximum step size allowed to ODE solver.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.

maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.
nan_fac	A penalty for each data point the model is not able to simulate. We recommend higher than 0 and smaller than 1.

Details

Check [CellNOptR](#) for details about the cno1ist and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a function to evaluate the model fitness. This function receives a continuous parameter vector.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [createLBodeContPars](#)

Examples

```
library(CNORode)
data("ToyCN01ist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");

ode_parameters=createLBodeContPars(model, random=TRUE);
minlp_obj_function=getLBodeMINLPobjFunction(cno1istCNORodeExample, model,ode_parameters,indices);

n_int_vars=dim(model$interMat)[2];
x_int=round(runif(n_int_vars))
x_cont=ode_parameters$parValues;
x=c(x_cont,x_int);
f=minlp_obj_function(x);
```

getLBodeModelSim

Simulate the logic-based ODE model

Description

This function simulates a logic-based ODE model and return a list with one matrix for each time point. The input species in the model are filled with NA values. If the simulation of a particular set of initial conditions fails the solver will fill the experience row with NA values.

Usage

```
getLBodeModelSim(cnolist, model, ode_parameters = NULL, indices = NULL, timeSignals=NULL,
time = 1, verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001, maxStepSize = Inf,
maxNumSteps = 1e+05, maxErrTestsFails = 50)
```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with indexFinder function from CellNOptR .
timeSignals	An array containing a different timeSignals. If you use this argument, it will also modify the dimensions from valueSignals.
time	An integer with the index of the time point to start the simulation. Default is 1.
verbose	A logical value that triggers a set of comments.
transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.
maxStepSize	The maximum number of internal steps between two points being sampled before the solver fails.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.
maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.

Details

Check [CellNOptR](#) for details about the cnolist and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a list with simulated data with similar structure to `cnolist$valueSignals`. Contains one matrix for each time-point. Each matrix contains one row per experiment and one columns per model species.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars](#)

Examples

```
library(CNORode)
data('ToyCNolist',package='CNORode');
data('ToyModel',package='CNORode');
data('ToyIndices',package='CNORode');
modelSimulation=getLBodeModelSim(cnolistCNORodeExample, model,indices=indices);
```

getLBodeSimFunction *Get a function to simulate a logic based ODE model.*

Description

This function is internally used by CNORode to configure the simulation function with default arguments.

Usage

```
getLBodeSimFunction(cnolist1, model1, adjMatrix1, indices1, odeParameters1,
time1 = 1, verbose1 = 0, transfer_function1 = 3, reltol1 = 1e-04, atol1 = 0.001,
maxStepSize1 = Inf, maxNumSteps1 = 1e+05, maxErrTestsFails1 = 50,
initial_state1=0.1)
```

Arguments

cnolist1	A list containing the experimental design and data.
model1	The logic model to be simulated.
adjMatrix1	An adjacency matrix from the model.
indices1	Indices to map data in the model. Obtained with indexFinder function from CellNOptR.
odeParameters1	A list with the ODEs parameter information. Obtained with createLBodeContPars .
time1	An integer with the index of the time point to start the simulation. Default is 1.
verbose1	A logical value that triggers a set of comments.
transfer_function1	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol1	Relative Tolerance for numerical integration.
atol1	Absolute tolerance for numerical integration.
maxStepSize1	The maximum step size allowed to ODE solver.
maxNumSteps1	The maximum number of internal steps between two points being sampled before the solver fails.

`maxErrTestsFails1` Specifies the maximum number of error test failures permitted in attempting one step.

`initial_state1` initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Value

A function that returns a simulated model.

Note

This function is for CNORode internal use.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR CNORode](#)

getStates

Find which species in the model are states.

Description

Receives an adjacency matrix (`model$interMat` from `CellNOptR`) and finds which species are states (i.e. not inputs).

Usage

```
getStates(adjacency)
```

Arguments

`adjacency` An adjacency matrix from the model.

Value

A numeric vector with 0's for positions which are states and 1's for positions which are.

Note

For internal use of CNORode.

Author(s)

David Henriques, Thomas Cokelaer

See Also[incidence2Adjacency](#)

incidence2Adjacency *Convert an incidence matrix into an adjacency matrix.*

Description

Convert the incidence matrix (model representation of CellNOptR) into an adjacency matrix. Denotes the inputs/output relationships.

Usage

```
incidence2Adjacency(model)
```

Arguments

model Model from CellNOptR.

Value

Directed Adjacency matrix of size n_species by n_species.

Note

For internal use of CNORode.

Author(s)

David Henriques, Thomas Cokelaer

See Also[CellNOptR](#)

indices *Indices that relate cnoList to model*

Description

A list with indices that relate the cnoList with the model from CellNOptR

minlpLBodeSSm	<i>Search for the best combination of continuous parameters and logic gates.</i>
---------------	--

Description

This function uses `essR` to search for the best set of continuous parameters and model structure. The objective function is the same as the one provided by [getLBodeMINLPObjFunction](#).

Usage

```
minlpLBodeSSm(cnolist, model, ode_parameters = NULL, int_x0=NULL, indices = NULL, maxeval = Inf,
maxtime = 100, ndiverse = NULL, dim_refset = NULL, local_solver = NULL, time = 1,
verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001, maxStepSize = Inf,
maxNumSteps = 1e+05, maxErrTestsFails = 50, nan_fac = 1)
```

Arguments

<code>cnolist</code>	A list containing the experimental design and data.
<code>model</code>	The logic model to be simulated.
<code>ode_parameters</code>	A list with the ODEs parameter information. Obtained with createLBodeContPars .
<code>int_x0</code>	Vector with initial solution for integer parameters.
<code>indices</code>	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
<code>maxeval</code>	Maximum number of evaluation in the optimization procedure.
<code>maxtime</code>	Maximum number of evaluation spent in optimization procedure.
<code>ndiverse</code>	Duration of the optimisation procedure.
<code>dim_refset</code>	Number of diverse initial solutions.
<code>local_solver</code>	Local solver to be used in SSm.
<code>time</code>	An integer with the index of the time point to start the simulation. Default is 1.
<code>verbose</code>	A logical value that triggers a set of comments.
<code>transfer_function</code>	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and for normalized Hill function.
<code>reltol</code>	Relative Tolerance for numerical integration.
<code>atol</code>	Absolute tolerance for numerical integration.
<code>maxStepSize</code>	The maximum step size allowed to ODE solver.
<code>maxNumSteps</code>	The maximum number of internal steps between two points being sampled before the solver fails.
<code>maxErrTestsFails</code>	Specifies the maximum number of error test failures permitted in attempting one step.
<code>nan_fac</code>	A penalty for each data point the model is not able to simulate. We recommend higher than 0 and smaller than 1.

Details

Check [CellNOptR](#) for details about the cno1ist and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

LB_n	A numeric value to be used as lower bound for all parameters of type n.
LB_k	A numeric value to be used as lower bound for all parameters of type k.
LB_tau	A numeric value to be used as lower bound for all parameters of type tau.
UB_n	A numeric value to be used as upper bound for all parameters of type n.
UB_k	A numeric value to be used as upper bound for all parameters of type k.
UB_tau	A numeric value to be used as upper bound for all parameters of type tau.
default_n	The default parameter to be used for every parameter of type n.
default_k	The default parameter to be used for every parameter of type k.
default_tau	The default parameter to be used for every parameter of type tau.
LB_in	An array with the the same length as ode_parameters\$parValues with lower bounds for each specific parameter.
UB_in	An array with the the same length as ode_parameters\$parValues with upper bounds for each specific parameter.
opt_n	Add all parameter n to the index of parameters to be fitted.
opt_k	Add all parameter k to the index of parameters to be fitted.
opt_tau	Add all parameter tau to the index of parameters to be fitted.
random	A logical value that determines that a random solution is for the parameters to be optimised.
model	The best fitting found model structure.
smm_results	A list containing the information provided by the nonlinear optimization solver.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars](#) `essR`

Examples

```
## Not run:
data("ToyCNO1ist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");

ode_parameters=createLBodeContPars(model, random=TRUE);
```

```

#Visualize initial solution
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,ode_parameters,indices=indices)
ode_parameters=minlpLBodeSSm(cnolistCNORodeExample, model,ode_parameters);

model=ode_parameters$model;

#Visualize fitted solution
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,indices=indices);

## End(Not run)

```

model	<i>A model from CellNoptR</i>
-------	-------------------------------

Description

A model from CellNoptR to use with provided examples

parEstimationLBode	<i>Perform parameter estimation using a genetic algorithm (package <code>genalg</code>) or <code>ssm</code> (if package <code>essm</code> available).</i>
--------------------	---

Description

This function is an alias to the parEstimationLBode variants ([parEstimationLBodeGA](#) and [parEstimationLBodeSSm](#))

Usage

```
parEstimationLBode(cnolist, model, method="ga", ode_parameters = NULL, indices = NULL,
  paramsGA=NULL, paramsSSm=NULL)
```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
method	Only "ga" or "essm" arguments are accepted.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with <code>indexFinder</code> function from CellNoptR.
paramsGA	A list of GA parameters. default is the list returned by <code>defaultParametersGA</code> .
paramsSSm	A list of SSm parameters. default is the list returned by <code>defaultParametersSSm</code> .

Value

LB_n	A numeric value to be used as lower bound for all parameters of type n.
LB_k	A numeric value to be used as lower bound for all parameters of type k.
LB_tau	A numeric value to be used as lower bound for all parameters of type tau.
UB_n	A numeric value to be used as upper bound for all parameters of type n.
UB_k	A numeric value to be used as upper bound for all parameters of type k.
UB_tau	A numeric value to be used as upper bound for all parameters of type tau.
default_n	The default parameter to be used for every parameter of type n.
default_k	The default parameter to be used for every parameter of type k.
default_tau	The default parameter to be used for every parameter of type tau.
LB_in	An array with the the same length as ode_parameters\$parValues with lower bounds for each specific parameter.
UB_in	An array with the the same length as ode_parameters\$parValues with upper bounds for each specific parameter.
opt_n	Add all parameter n to the index of parameters to be fitted.
opt_k	Add all parameter k to the index of parameters to be fitted.
opt_tau	Add all parameter tau to the index of parameters to be fitted.
random	A logical value that determines that a random solution is for the parameters to be optimized.
res	A list containing the information provided by the solver.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars rbga](#)

Examples

```
data("ToyCN0list", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");

ode_parameters=createLBodeContPars(model, random=TRUE);
#Visualize initial solution
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,ode_parameters,indices=indices)
paramsGA = defaultParametersGA()
paramsGA$maxStepSize = 1
paramsGA$popSize = 10
paramsGA$iter = 10
paramsGA$transfer_function = 2

ode_parameters=parEstimationLBode(cnolistCNORodeExample,model,ode_parameters=ode_parameters,
```

```

paramsGA=paramsGA)
#Visualize fitted solution
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,ode_parameters,indices=indices)

```

parEstimationLBodeGA *Perform parameter estimation using a genetic algorithm (package genalg).*

Description

This function uses a genetic algorithm (package genalg) to perform parameter estimation. The objective function is the same as the one provided by [getLBodeContObjFunction](#).

Usage

```

parEstimationLBodeGA(cnolist, model, ode_parameters = NULL, indices = NULL, mutationChance = NA, popSize = 100, elitism = NA, time = 1, monitor = TRUE, verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001, maxStepSize = Inf, maxNumSteps = 1e+05, maxErrTestsFails = 50, nan_fac = 1, initial_state=0.1)

```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with indexFinder function from CellNOptR.
mutationChance	the chance that a gene in the chromosome mutates. By default $1/(size+1)$. It affects the convergence rate and the probing of search space: a low chance results in quicker convergence, while a high chance increases the span of the search space.
popSize	the population size.
iters	the number of iterations.
elitism	the number of chromosomes that are kept into the next generation. By default is about 20% of the population size
time	An integer with the index of the time point to start the simulation. Default is 1.
monitor	If TRUE a plot will be generated to monitor the objective function
verbose	A logical value that triggers a set of comments.
transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.

maxStepSize	The maximum step size allowed to ODE solver.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.
maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.
nan_fac	A penalty for each data point the model is not able to simulate. We recommend higher than 0 and smaller than 1.
initial_state	initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Value

LB_n	A numeric value to be used as lower bound for all parameters of type n.
LB_k	A numeric value to be used as lower bound for all parameters of type k.
LB_tau	A numeric value to be used as lower bound for all parameters of type tau.
UB_n	A numeric value to be used as upper bound for all parameters of type n.
UB_k	A numeric value to be used as upper bound for all parameters of type k.
UB_tau	A numeric value to be used as upper bound for all parameters of type tau.
default_n	The default parameter to be used for every parameter of type n.
default_k	The default parameter to be used for every parameter of type k.
default_tau	The default parameter to be used for every parameter of type tau.
LB_in	An array with the the same length as ode_parameters\$parValues with lower bounds for each specific parameter.
UB_in	An array with the the same length as ode_parameters\$parValues with upper bounds for each specific parameter.
opt_n	Add all parameter n to the index of parameters to be fitted.
opt_k	Add all parameter k to the index of parameters to be fitted.
opt_tau	Add all parameter tau to the index of parameters to be fitted.
random	A logical value that determines that a random solution is for the parameters to be optimized.
res	A list containing the information provided by the nonlinear optimization solver (genalg).

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars rbga](#)

Examples

```

data("ToyCNolist",package="CNORode");
data("ToyModel",package="CNORode");
data("ToyIndices",package="CNORode");

ode_parameters=createLBodeContPars(model,random=TRUE);
#Visualize initial simulation
#simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,ode_parameters,indices=indices)

ode_parameters=parEstimationLBodeGA(cnolistCNORodeExample,model,ode_parameters=ode_parameters,
indices=indices,maxStepSize=1,atol=1e-3,reltol=1e-5,transfer_function=2,popSize=10,iter=40);

#Visual solution after optimization
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,indices=indices,ode_parameters=ode_parameters);

```

parEstimationLBodeSSm *Perform parameter estimation using essR.*

Description

This function uses `essR` to perform parameter estimation. The objective function is the same as the one provided by [getLBodeContObjFunction](#).

Usage

```

parEstimationLBodeSSm(cnolist, model, ode_parameters = NULL, indices = NULL,
maxeval = Inf, maxtime = 100, ndiverse = NULL, dim_refset = NULL, local_solver = NULL,
time = 1, verbose = 0, transfer_function = 3, reltol = 1e-04, atol = 0.001,
maxStepSize = Inf, maxNumSteps = 1e+05, maxErrTestsFails = 50, nan_fac =1,
useVariances=F,initial_state=0.1)

```

Arguments

<code>cnolist</code>	A list containing the experimental design and data.
<code>model</code>	The logic model to be simulated.
<code>ode_parameters</code>	A list with the ODEs parameter information. Obtained with createLBodeContPars .
<code>indices</code>	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
<code>maxeval</code>	Maximum number of evaluation in the optimization procedure.
<code>maxtime</code>	Duration of the optimization procedure.
<code>ndiverse</code>	Number of diverse initial solutions.
<code>dim_refset</code>	Size of the reference set.
<code>local_solver</code>	Local solver to be used in SSm.
<code>time</code>	An integer with the index of the time point to start the simulation. Default is 1.
<code>verbose</code>	A logical value that triggers a set of comments.

transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.
maxStepSize	The maximum step size allowed to ODE solver.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.
maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.
nan_fac	A penalty for each data point the model is not able to simulate. We recommend higher than 0 and smaller than 1.
useVariances	Uses variance if any
initial_state	initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Details

Check [CellNOptR](#) for details about the codelist and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

LB_n	A numeric value to be used as lower bound for all parameters of type n.
LB_k	A numeric value to be used as lower bound for all parameters of type k.
LB_tau	A numeric value to be used as lower bound for all parameters of type tau.
UB_n	A numeric value to be used as upper bound for all parameters of type n.
UB_k	A numeric value to be used as upper bound for all parameters of type k.
UB_tau	A numeric value to be used as upper bound for all parameters of type tau.
default_n	The default parameter to be used for every parameter of type n.
default_k	The default parameter to be used for every parameter of type k.
default_tau	The default parameter to be used for every parameter of type tau.
LB_in	An array with the the same length as ode_parameters\$parValues with lower bounds for each specific parameter.
UB_in	An array with the the same length as ode_parameters\$parValues with upper bounds for each specific parameter.
opt_n	Add all parameter n to the index of parameters to be fitted.
opt_k	Add all parameter k to the index of parameters to be fitted.
opt_tau	Add all parameter tau to the index of parameters to be fitted.
random	A logical value that determines that a random solution is for the parameters to be optimized.
smm_results	A list containing the information provided by the nonlinear optimization solver.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [createLBodeContPars](#)

Examples

```
## Not run:
data("ToyCNolist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");

ode_parameters=createLBodeContPars(model, random=TRUE);

#Visualize intial simulation
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,ode_parameters,indices=indices)

ode_parameters=parEstimationLBodeSSm(cnolistCNORodeExample,model,ode_parameters,
indices=indices,maxtime=20,ndiverse=50,dim_refset=6);

#Visualize fitterd solution
simulatedData=plotLBodeFitness(cnolistCNORodeExample, model,indices=indices,ode_parameters=ode_parameters);

## End(Not run)
```

plotLBodeFitness *Plot data against simulated values.*

Description

Plots the simulated values with the logic-based ODE against the the data contained contained the data contained in the cnolist. The data values are represented with a black line and the simulated values with a blue line. Additionally this functions returns the the simulated values.

Usage

```
plotLBodeFitness(cnolist, model, ode_parameters = NULL, indices = NULL,
  adjMatrix = NULL, time = 1, verbose = 0, transfer_function = 3, reltol = 1e-04,
  atol = 0.001, maxStepSize = Inf, maxNumSteps = 1e+05, maxErrTestsFails = 50,
  plot_index_signals = NULL, plot_index_experiments = NULL,
  plot_index_cues = NULL, colormap="heat", plotParams=list(margin=0.1, width=15, height=12,
  cmap_scale=1, cex=1.6, ymin=NULL), initial_state=0.1 )
```


Arguments

<code>cnolist</code>	A list containing the experimental design and data.
<code>model</code>	The logic model to be simulated.
<code>ode_parameters</code>	A list with the ODEs parameter information. Obtained with createLBodeContPars .
<code>indices</code>	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
<code>adjMatrix</code>	Model representation in the form of an adjacency matrix. When not provided will be automatically computed based in the model.
<code>time</code>	An integer with the index of the time point to start the simulation. Default is 1.
<code>verbose</code>	A logical value that triggers a set of comments.
<code>transfer_function</code>	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
<code>reltol</code>	Relative Tolerance for numerical integration.
<code>atol</code>	Absolute tolerance for numerical integration.
<code>maxStepSize</code>	The maximum step size allowed to ODE solver.
<code>maxNumSteps</code>	The maximum number of internal steps between two points being sampled before the solver fails.
<code>maxErrTestsFails</code>	Specifies the maximum number of error test failures permitted in attempting one step.
<code>plot_index_signals</code>	In case you only want to plot some signals, provide an integer vector with the indexes.
<code>plot_index_experiments</code>	In case you only want to plot some experiments, provide an integer vector with the indexes.
<code>plot_index_cues</code>	In case you only want to plot some cues, provide an integer vector with the indexes.
<code>colormap</code>	Uses the same colormap as in <code>CellNOptR</code> by default. If set to "green", it uses the deprecated colormap.
<code>plotParams</code>	additional parameters to refine the ploggin. See <code>plotOptimResultsPan</code> function in <code>CellNOptR</code> for more details.
<code>initial_state</code>	initial state of the dynamic nodes (non-measured) (Defaults to 0.1)

Details

Check [CellNOptR](#) for details about the `cnolist` and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a list with simulated data that has the same structure as the `cnolist$valueSignals`. One matrix for each time-point.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars](#)

Examples

```
library(CNORode)
data("ToyCNolist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");
ode_parameters=createLBodeContPars(model, random=TRUE);
dataSimulation=plotLBodeFitness(cnolistCNORodeExample, model, indices=indices);
```

plotLBodeModelSim	<i>Simulate the model and plot the obtained with the different experimental conditions.</i>
-------------------	---

Description

Plots the simulated values of the logic based ODE model. Only dynamic states are plotted, i.e. those that are not inputs. a blue line. Additionally this functions returns the the simulated values.

Usage

```
plotLBodeModelSim(cnolist, model, ode_parameters = NULL, indices = NULL,
adjMatrix = NULL, timeSignals=NULL, time = 1, verbose = 0, transfer_function = 3,
reltol = 1e-04, atol = 0.001, maxStepSize = Inf, maxNumSteps = 1e+05,
maxErrTestsFails = 50, large = FALSE, nsplit = 4, show=T)
```

Arguments

cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.
ode_parameters	A list with the ODEs parameter information. Obtained with createLBodeContPars .
indices	Indices to map data in the model. Obtained with indexFinder function from CellNOptR.
adjMatrix	Model representation in the form of an adjacency matrix. When not provided will be automatically computed based in the model.
timeSignals	An array containing a different timeSignals. If you use this argument, it will also modify the dimensions from valueSignals.
time	An integer with the index of the time point to start the simulation. Default is 1.
verbose	A logical value that triggers a set of comments.

transfer_function	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
reltol	Relative Tolerance for numerical integration.
atol	Absolute tolerance for numerical integration.
maxStepSize	The maximum step size allowed to ODE solver.
maxNumSteps	The maximum number of internal steps between two points being sampled before the solver fails.
maxErrTestsFails	Specifies the maximum number of error test failures permitted in attempting one step.
large	Boolean variable defining if the plot should split into several subplots.
nsplit	In case the large plot options is selected define how many subplots will exist. Default is 4.
show	show the error (defaults to TRUE)

Value

Returns a list with simulated Model values. One matrix of size number of species by number of experimental conditions for each time-point.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellN0ptR createLBodeContPars](#)

Examples

```
library(CNORode)
data("ToyCNolist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");
modelSimulation=plotLBodeModelSim(cnolistCNORodeExample, model, indices=indices);
```

simdata2cnolist *converts output of getLBodeModelSim to cnolist*

Description

This function converts the simulated data returned by getLBodeModelSim into a valid CNolist data structure.

Usage

```
simdata2cnolist(sim_data, cnolist, model)
```

Arguments

sim_data	structure returned by getLBodeModelSim
cnolist	A list containing the experimental design and data.
model	The logic model to be simulated.

Value

a CNolist

Author(s)

Thomas Cokelaer

See Also

[CellNOptR createLBodeContPars](#)

Examples

```
data('ToyCNolist', package='CNORode');
data('ToyModel', package='CNORode');
data('ToyIndices', package='CNORode');
simdata = getLBodeModelSim(cnolistCNORodeExample, model, indices=indices)
cnolist = simdata2cnolist(simdata, cnolistCNORodeExample, model)

cnolist = simdata2cnolist(simdata, cnolistCNORodeExample, model)
```

simulate

Simulate value signals a CNO list With Logic-Based ODEs.

Description

This function receives a set of inputs, namely the cnolist and the model and returns a list with the same size of the cnolist\$valueSignals.

Usage

```
simulate(cnolist, model, ode_parameters=NULL, indices=NULL,
adjMatrix=NULL, time=1, verbose=0, transfer_function=3,
reltol=1e-04, atol=0.001, maxStepSize=Inf, maxNumSteps=1e+05,
maxErrTestsFails=50)
```

Arguments

<code>cnolist</code>	A list containing the experimental design and data.
<code>model</code>	A list with the ODEs parameter information. Obtained with createLBodeContPars .
<code>ode_parameters</code>	A list with the ODEs parameter information. Obtained with <code>makeParameterList</code> function.
<code>indices</code>	Indices to map data in the model. Obtained with <code>indexFinder</code> function from <code>CellNOptR</code> .
<code>adjMatrix</code>	The adjacency matrix. Recomputed if not provided
<code>time</code>	An integer with the index of the time point to start the simulation. Default is 1.
<code>verbose</code>	A logical value that triggers a set of comments.
<code>transfer_function</code>	The type of used transfer. Use 1 for no transfer function, 2 for Hill function and 3 for normalized Hill function.
<code>reltol</code>	Relative Tolerance for numerical integration.
<code>atol</code>	Absolute tolerance for numerical integration.
<code>maxStepSize</code>	The maximum step size allowed to ODE solver.
<code>maxNumSteps</code>	The maximum number of internal steps between two points being sampled before the solver fails.
<code>maxErrTestsFails</code>	Specifies the maximum number of error test failures permitted in attempting one step.

Details

Check [CellNOptR](#) for details about the `cnolist` and the model format. For more details in the configuration of the ODE solver check the CVODES manual.

Value

Returns a list with simulated data that has the same structure as the `cnolist$valueSignals`. One matrix for each time-point.

Author(s)

David Henriques, Thomas Cokelaer

See Also

[CellNOptR](#) [parEstimationLBode](#) [parEstimationLBodeSSm](#)

Examples

```
library(CNORode)
data("ToyCNolist", package="CNORode");
data("ToyModel", package="CNORode");
data("ToyIndices", package="CNORode");
dataSimulation = simulate(cnolistCNORodeExample, model, indices=indices);
```

Index

- *Topic **CNORode**
 - CNORode, 2
- *Topic **CVODES**
 - getLBodeSimFunction, 13
- *Topic **CellNOptR**
 - parEstimationLBode, 18
 - parEstimationLBodeGA, 20
- *Topic **SSm**
 - defaultParametersSSm, 6
- *Topic **adjacency**
 - getStates, 14
 - incidence2Adjacency, 15
- *Topic **algorithm**
 - defaultParametersGA, 5
 - parEstimationLBode, 18
 - parEstimationLBodeGA, 20
- *Topic **default**
 - defaultParametersGA, 5
 - defaultParametersSSm, 6
- *Topic **essR**
 - defaultParametersSSm, 6
- *Topic **genetic**
 - defaultParametersGA, 5
 - parEstimationLBode, 18
 - parEstimationLBodeGA, 20
- *Topic **incidence**
 - incidence2Adjacency, 15
- *Topic **logic**
 - parEstimationLBode, 18
 - parEstimationLBodeGA, 20
- *Topic **matrix**
 - incidence2Adjacency, 15
- *Topic **model**
 - parEstimationLBode, 18
 - parEstimationLBodeGA, 20
- *Topic **parameters**
 - defaultParametersGA, 5
- *Topic **states**
 - getStates, 14
- CellNOptR, 3, 5, 6, 8, 9, 11–15, 17, 19, 21, 23–29
- cnolistCNORodeExample, 2
- CNORode, 2, 14
- createLBodeContPars, 3, 7–13, 16–22, 24–29
- defaultParametersGA, 5
- defaultParametersSSm, 6
- getLBodeContObjFunction, 7, 20, 22
- getLBodeDataSim, 8
- getLBodeMINLPobjFunction, 10, 16
- getLBodeModelSim, 3, 11
- getLBodeSimFunction, 13
- getStates, 14
- incidence2Adjacency, 15, 15
- indices, 15
- minlpLBodeSSm, 16
- model, 18
- parEstimationLBode, 3, 5, 6, 9, 18, 29
- parEstimationLBodeGA, 5, 18, 20
- parEstimationLBodeSSm, 6, 9, 18, 22, 29
- plotLBodeFitness, 3, 24
- plotLBodeModelSim, 26
- rbga, 19, 21
- simdata2cnolist, 27
- simulate, 28